



APC-2

AUTOMATED SWITCHING SYSTEM



Current Sensing Outlet Switcher

- Gives virtually any A/V component a switched AC outlet
- Current Sense-Triggered
- Individually boxed

120Volt AC Power Switching System



APC-2

Stock Number
FG00254

FEATURES

- Three AC outlets—one current sensing (requires min. 30W current draw differential between on/off for reliable sensing), one switched, one unswitched - 1,500W maximum (all outlets combined)
- APC-2 is activated by current sensing outlet or 12Volt DC signal (100mA minimum)
- 12Volt control output for activating other Niles devices such as the SPK-1, AVS-2, AC-3, or RFS-1
- N.O. (normally open) and N.C. (normally closed) relay contacts for controlling other devices such as electric screens, motorized lifts, drapes, etc.
- Relay contacts rated at one amp, 30V max. AC/DC

SPECIFICATIONS

- Dimensions: 8" wide x 2-3/4" high x 7" deep

Warranty: Two-year limited

Product Detail

Use a TV to power ON a surround sound system with the current sensing outlet of the APC-2.

