

### Key Features

- 5 Disc SA-CD/CD Changer
- Time Alignment Function for Optimum SA-CD Playback
- Multi-Channel Audio Output
- Dual Laser Assembly Optimized for SA-CD /CD Playback
- CD/CD-R/CD-RW Playback Capability<sup>1</sup>
- SA-CD Text/CD Text Capability

5 DISC CHANGER



SUPER AUDIO CD



COMPACT  
disc  
DIGITAL AUDIO



CD-R/RW  
PLAY BACK



# SCD-CE595

## Super Audio CD® Player

### Specifications

---

#### Audio

Frequency Range: 2 Hz - 100kHz

Frequency Response: 2Hz- 50kHz (-3dB)

Dynamic Range: >100dB

Harmonic Distortion: <0.0035%

Wow and Flutter: Below Measurement Limit (+/- 0.001% W-Peak)

Digital-to-Analog Converter: Super Audio D/A

Frequency Response: 2 Hz - 20kHz (+/- 0.5dB)

Dynamic Range: CD- more than 99dB

Harmonic Distortion: CD- Less than 0.0039%

Wow and Flutter: CD- Below Measurement Limit (+/-0.001% W-Peak)

Open Circuit Output Level: Digital Opt: -18dB(fix),  
Analog Balance: 2Vrms (fix)

#### Inputs and Outputs

Analog Audio Output(s): 2 Channels, 5.1 Channels

Digital Audio Output(s): CD Only

#### Power

Power Consumption: 15W

Power Requirements: AC 120V, 60Hz

### SCD-CE595

#### Weight

12 lbs (5.4 Kg)

#### Dimensions (WHD)

17 x 4 1/3 x 16 8/15" (432 x 110 x 420mm)

#### UPC Code

0272426432390

---

1. CD-R/RW playback may not be compatible with all discs, depending on recording conditions.

©2004 Sony Electronics Inc.

Sony, Direct Stream Digital, Jog Dial, and Super Audio CD are trademarks of Sony. All other trademarks are the property of their respective owners.

Features and specifications are subject to change without notice.

Non-metric weights and measures are approximate.