

ELAC The life of sound.



A powerful
app to control
powerful bass.

Debut
S10EQ
by Andrew Jones.

10-inch
400-Watt*
Powered
Subwoofer



ELAC Debut by Andrew Jones.

S10EQ 10-inch 400-Watt* Powered Subwoofer



Do you like bass? Advanced Bluetooth® control and Auto EQ let you operate the Debut S10EQ from your smartphone. A 10-inch bass driver, powered by a 400-Watt* BASH amplifier and enhanced by a 10-inch passive radiator, creates awesome low frequencies and a stunning sense of realism.

Advanced Bluetooth® Control

Doing away with traditional analog controls, the subwoofer incorporates our advanced digital control system. Simply download the ELAC SubEQ app for your smartphone** and you have complete control. No more fumbling around the back of the subwoofer again.



Auto EQ

Utilizing our SubEQ app and your smartphone's microphone, the subwoofer will automatically EQ itself to your room's unique characteristics using a 12-Band parametric equalizer. Full manual EQ is available as well.

Custom Driver

A custom 10-inch long-throw driver provides the quality and quantity of bass that is fundamental to accurately reproducing today's demanding movie soundtracks and music. A 10-inch passive radiator improves the transient response and increases the efficiency of the system.

BASH® Amplifier

All ELAC subwoofers utilize BASH tracking amplifiers. Unlike conventional amplifiers, BASH amplifiers track the input signal and adjust the available supply voltage to a traditional Class AB amplifier. This makes the amplifier incredibly efficient but also provides the on-demand power needed for dynamic movies and music.

Braced MDF Cabinet

A horizontal center brace strengthens and stiffens the cabinet, helping minimize unwanted vibrations that can discolor music or movie content.

Auto Power On/Off

The subwoofer will detect when an audio signal is being sent to the amplifier and will power on. Also, to conserve energy, the subwoofer will power off after a long period of inactivity.

S10EQ Specifications

SPEAKER TYPE	Powered bass-reflex subwoofer with passive radiator
AMPLIFIER TYPE	BASH—Tracking
MAXIMUM AMPLIFIER POWER	400 Watts peak / 200 Watts RMS
FREQUENCY RESPONSE	28 to 150 Hz
CROSSOVER FREQUENCY	50 to 150 Hz, continuously adjustable
DRIVER	10-inch high-excursion doped paper cone
PASSIVE RADIATOR	10-inch high-excursion doped paper cone
STANDBY POWER CONSUMPTION5 Watts
CABINET	CARB2 rated MDF
CABINET FINISH	Black brushed vinyl
INPUTS	LFE RCA
WIDTH	13.5 in / 343 mm
HEIGHT	13.5 in / 343 mm
DEPTH	13.5 in / 343 mm
NET WEIGHT	31.0 lb / 14.1 kg
GROSS WEIGHT (PACKAGED)	35.0 lb / 15.9 kg

*400 Watts Peak Power / 200 Watts RMS Power

**A Bluetooth 4.0 low-energy Android or IOS device is required to set up and operate this subwoofer.