



marantz



A/V Pre-amp with State-of-the-Art Audio & Video Playback Technologies

For the ultimate music and home theater surround sound experience, the Marantz AV8801 A/V pre-amplifier is packed with the latest state-of-the-art audio and video technologies, including the highest resolution audio formats such as Dolby TrueHD and DTS HD Master Audio. As well, the AV8801 features the ability to expand beyond conventional 5.1 and 7.1 channel configurations, thanks to the inclusion of DTS Neo:X and Audyssey DSX technology, which provides up to 11.2 channel playback, with additional front width and front height channels for the most immersive surround sound experience you've ever heard. The video section features a host of video inputs, with a sophisticated video processor that provides upconversion from standard definition (SD) and high definition (HD) video to the latest Ultra High Definition (4K) format (3840x2160 pixels) for full compatibility with next generation Ultra High Definition (4K) displays. There are 7 HDMI inputs and 3 HDMI outputs, with dual HDMI output for the main zone that outputs the same signal to two displays, such as a flat panel TV and a front projector. A third HDMI output lets you enjoy another program in another room. Equipped with Audyssey MultEQ XT32, the AV8801 automatically configures key acoustical parameters and optimizes total system response. Full networking functionality includes 4 Ethernet ports along with available iOS and Android mobile control apps.

Audio/Video Quality

- 11.2 channel dedicated A/V pre-amplifier
- 11.2 channel enhanced surround processing with Audyssey DSX and DTS Neo:X

Current feedback & HDAM pre-amplifier circuitry with massive power supply by full shielded toroidal transformer for superior sound

- 4K video support (pass through and GUI overlay)
- 4K (3840 × 2160) upscaling via HDMI

New smoothest diagonal edge video interpolation
 Audyssey MultEQ XT32 and Audyssey Sub EQ
 HT Dual subwoofer EQ processing for optimum room acoustic calibration

Audyssey LFC solves the problem of low frequency sounds disturbing people in adjacent rooms
 Supports 192 kHz high resolution network audio (WAV 192 kHz/24-bit, FLAC 192 kHz/24-bit, ALAC 96 kHz/24 bit)

Gapless audio playback

Connectivity, Flexibility & Expandability

 AirPlay: Stream music from your iPad, iPhone or iPod touch or from your iTunes music library
 Networking: Stream internet radio, Pandora, SiriusXM internet radio, Spotify, as well as music and photos over the home network

- Includes an Ethernet hub (4 ports) for easy connection to network devices on your home network
 Bluetooth wireless connectivity (M-XPort) via
- optional RX-101 adaptor
- 11.2ch XLR balanced preoutputs

■ Front HDMI port supports MHLTM

(Mobile High Definition Link) for viewing smartphone content on your HDTV

- 2 ports (front, rear selectable) USB input direct
- digital play for iPod, iPhone and USB drives 7 (front: 1) /3 HDMI In/Out -Pass through in standby mode

-Dual HDMI outputs allows two connected dis play devices (e.g. TV and projector) and outputs the same source simultaneously -Zone4 HDMI output allows a different source to be output to another room

- Supports HDMI (3D, ARC, Deep Color, "x.v.Color", Auto Lip Sync, 4K, and HDMI control function)
- Audyssey Dynamic EQ & Dynamic Volume
- 3/2 (gold plated) Component In/Out
- 2/2 Optical/Coaxial (gold plated) Digital In
- Headphone output
- HD Radio (AM/FM) tuner built-in
- 7 Audio inputs (incl. front input) and
- an output (gold plated)
- Phono input (gold plated)
- XLR balanced audio input

Ease of Use

- Improved System Setup with menu assist
- Rich overlay GUI with English, French, or Spanish
- New LCD Learning Remote control

 Mobile App control with advanced media browsing (iOS & Android)

Additional Features

InstaPrevue provides live picture-in-picture of connected HDMI sources

- 4 source 4 zone capability
- RS232C control (AMX/Crestron command)
- Control4 certified (IP control)
- Assignable DC trigger (+12 V, 150 mA x 2)
- Audyssey Installer Ready

Marantz Audio Advantages

- Hybrid PLL jitter reducer for accurate audio clock
- M-DAX (Marantz Dynamic Audio eXpander)
- 192 kHz/32-bit audio DACs for all channels
- High grade build quality with 3 piece top cover
- Copper plated chassis
- because music matters

Specifications

Audio Section Analog

Input sensitivity/Input impedance Unbalanced input: 200 mV/47 k ohm Balanced input: 400 mV/94 k ohm Frequency response: 10 Hz – 100 kHz – +1, –3 dB (DIRECT mode) S/N: 105 dB (IHF-A weighted, DIRECT mode) Distortion: 0.005 % (20 Hz - 20 kHz) (DIRECT mode)

Rated output: Unbalanced pre-output: 1.2 V Balanced pre-output: 2.4 V

Digital

D/A output: Rated output - 2 V (at 0 dB playback) Total harmonic distortion - 0.008 % (1 kHz, at 0 dB) S/N ratio — 102 dB Dynamic range — 100 dB Digital input: Format - Digital audio interface Phono equalizer (PHONO input) Input sensitivity: 2.5 mV BIAA deviation: +1 dB (20 Hz to 20 kHz) S/N: 74 dB (A weighting, with 5 mV input) Rated output: 150 mV Distortion factor: 0.03 % (1 kHz, 3 V)

Y signal — 1 Vp-p, 75 ohm PB signal — 0.7 Vp-p, 75 ohm

PR signal — 0.7 Vp-p, 75 ohm Frequency response: 5 Hz – 60 MHz — 0, –3 dB

Input/output level and impedance: 1 Vp-p, 75 ohm

Frequency response: 5 Hz - 10 MHz 0, -3 dB

Color component video connector

Input/output level and impedance:

Tuner Section

Video Section

Standard video connectors

[FM]

(Note: μ V at 75 ohm , 0 dBf = 1 x 10⁻¹⁵ W) Receiving Range: 87.5 MHz – 107.9 MHz Usable Sensitivity: 1.5 µV (14.8 dBf) S/N: MONO 78 dB (IHF-A weighted, DIRECT mode) STEREO 68 dB (IHF-A weighted, DIRECT mode) HD 85 dB Total harmonic Distortion (at 1 kHz): MONO 0.1 % STEREO 0.2 % HD 0.02 %

[AM]

Receiving Range:AM: 530 kHz - 1710 kHz Usable Sensitivity: 20 µV S/N: HD 85 dB Total harmonic Distortion (at 1 kHz): HD 0.02 %

General

Power supply: AC 120 V, 60 Hz Power consumption: 90 W 0.2 W (Standby mode) 0.5 W (CEC standby mode) 5.1 W (network standby mode) Dimensions (W x H x D): 17 21/64" x 7 9/32" x 15 21/64" 440.0 x 185.0 x 389.3 mm Weight: 30 lbs 10 oz, 13.9 kg

Technology



• \bigcirc 0 0 0 0 0 0 6 0 0 .

*Design and specifications are subject to change without notice. *"Dolby", "Pro Logic" and the double-D symbol are trademarks of Dolby Laboratories. *DTS-HD, the Symbol & DTS-HD and the Symbol together are registered trademarks & DTS HD Master Audio is a trademark of Dolby Laboratories. *DTS-HD, the Symbol, & DTS-HD and the Symbol together are registered trademarks & DTS HD Master Audio is a trademark of Audyssey Laboratories. *HOML, the HDMI logo and High-Definition Hultimedia Interface are trademarks or registered trademarks of HOML Loensing LLC. *MHL, the MHL Logo, and Mobile High-Definition Link are trademarks or MHL LLC in the United States and other countries. *Windows Media and the Windows logo are trademarks or registered trademarks of Microsoft Corporation in SHIUS, XM and all related marks and logos are trademarks of Sinux XM Radio Inter, and its subsidiaries. All rights reserved. Service not available in Alaska and Havaii. "Windows Media for HDD Radio logo are proprietary trademarks of Higuly Digital Corp. *"Made for iPhone, "and mean that an electronic accessory with Pode, or iPhone, respectively, and has have not the doubler to meet Apple performance standards. Please note that the use of this accessory with Pode. "Rodo or iPhone, "And Heavie." *Apple is not responsible for the operation of this device or its compliance with safety and regulatory. *AirPlay, the AirPlay logo, iPhone, Pod, iPod classic, iPod nano, iPod shuffle, iPod touch and Tunes are trademarks of Apple Inc., registered in the U.S. and other countries.

©2012 Marantz America, LLC.

For purposes of improvement, specifications and design are subject to change without notice.All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, LLC, or any of its subsidiaries will not assume any liability for errors in this specifications. contained within this document.

1-855-ONE-MARANTZ